

STREET LIGHT INSERTS

This range of products is designed to retrofit into existing street lighting heads, replacing the lampholder and reflector assembly. The new gear tray can be installed in a very similar time to a lamp change and using the same tools. All the trays have UMSUG codes for local authority



TECHNICAL DETAILS

Part Number	Description	Circuit Watts (W)	Board Lumens	Luminaire Lumens
LPD2X12-12-4K ARC80	ARC 80 insert	12	1745	1640
LPD2X12-24-4K ARC80	ARC 80 insert	24	3490	3281
LPD2X12-48-4K ARC80	ARC 80 insert	48	6498	6108
LPD2X12-24-4K ARC90	ARC 90 insert	24	3490	3281
LPD2X12-48-4K ARC90	ARC 90 insert	48	6498	6108
LPD2X12-72-4K ARC90	ARC 90 insert	72	9747	9162
LPD2X12-12-4K IRIDIUM252	IRIDIUM 252 insert	12	1475	1640
LPD2X12-24-4K IRIDIUM252	IRIDIUM 252 insert	24	3490	3281
LPD2X12-24-4K IRIDIUM253	IRIDIUM 253 insert	24	3490	3281
LPD2X12-48-4K IRIDIUM253	IRIDIUM 253 insert	48	6498	6108
LPD2X12-48-4K IRIDIUM254	IRIDIUM 254 insert	48	6498	6108
LPD2X12-72-4K IRIDIUM254	IRIDIUM 254 insert	72	9747	9162
LPD2X12-12-4K URBIS	URBIS insert	12	1745	1640
LPD2X12-24-4K URBIS	URBIS insert	24	3490	3281
LPD2X12-12-4K PHOSCO P567	PHOSCO P567 insert	12	1745	1640
LPD2X12-24-4K PHOSCO P567	PHOSCO P567 insert	24	3490	3281
LPD2X12-12-4K THORN BETA-II	THORN BETA II insert	12	1745	1640
LPD2X12-24-4K THORN BETA-II	THORN BETA II insert	24	3490	3281
LPD2X12-12-4K MI36	MI36 insert	12	1745	1640
LPD2X12-24-4K MI36	MI36 insert	24	3490	3281



* When installed into the luminaire

PHOTOMETRIC

